



HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA

WAAS Satellite Changes: May 2022

The following maintenance tasks with the current operative WAAS satellites are expected during May 2022:

WAAS Satellite Maintenance Task Timeframe

PRN 135 Satellite	Entering Service	26 April 2022
PRN 138 Satellite	Ceasing Transmissions	17 May 2022

For complete details, see the [William J. Hughes Technical Center WAAS Test Team website](#). Specific dates for when PRN 135 enters service and PRN 138 is decommissioned will be posted to this website as they are determined.

Trimble-configured GNSS Solutions in North America that are set to use WAAS / SBAS / SBAS+ correction services must update the targeted correction satellite selection or their correction services will stop at some point in or after May 2022.

Trimble recommends that WAAS users experiencing issues to manually switch to PRN135.

Table of Contents for Manually Switching to PRN135:

Precision-IQ™ - XCN1050, XCN750, XCN2050	Page 2
FM-750™	Page 3
EZ-Guide® 250 and EZ- Guide® 500... ..	Page 4
Fm1000® and Fm1000+.....	Page 5
372 Receivers with CNH Pro/Intelliview Series	Page 6
AgRemote/RDI/Toolbox+ Configuration (AG-372, NAV-900 Receivers).....	Page 7
Delta Power Equipment Contact Information	Page 9




HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA


Instructions to Manually Change PRN

Precision-IQ™ - XCN1050, XCN750, XCN2050

1. From the Precision-IQ Home screen, tap the **GNSS** tile:



2. On the GNSS screen, tap the **Edit** button.
3. On the GNSS: Edit screen, tap **Setup**, then tap **Correction Satellite Selection**.
4. Choose **WAAS PRN 135** (or autoselect).






HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA

FM-750™

1. From the home screen select the **Settings** wrench.



2. On the Settings screen, select **GNSS/GPS**.



3. On the GNSS screen, select **GNSS Setup**.




4. On the GNSS Correction Source screen, select **WAAS/EGNOS** and tap green **Accept** button.
5. On the WAAS/EGNOS Settings screen, select **Satellite**.
6. On the Satellite screen, choose PRN135/WAAS135 and tap the green **Accept** button.



HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA

EZ-Guide® 250 and EZ-Guide 500

1. Select the **wrench** icon:
2. On the Configuration screen, select **System**.
3. On the System screen, select **GPS**.
4. On the GPS screen, select **GPS Setup**.
5. On the GPS Correction Source screen, select **WAAS / EGNOS**.



6. On the WAAS/EGNOS Settings screen, select **Satellite**.
7. On the Satellite screen, choose **WAAS135/PRN135**.






HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA

Fm1000® and Fm1000+ Integrated Display

1. Select the **Wrench/screwdriver** icon.
2. Select **GPS Receiver**, then **Diagnostics**.
3. Select **AgRemote**.
4. Enter the administration password: **2009**
5. Follow the instructions for AgRemote/RDI/Toolbox+ Configuration (AG-372, NAV-900 Receivers).






HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA

372 Receivers with CNH Pro/Intelliview Series


1. On the display press the **Back button** in the bottom right corner.
2. Go to **Diagnostics**.
3. Go across the bottom/side tabs to find **RDI**.
4. Follow the instructions for AgRemote/RDI/Toolbox+ Configuration (AG-372, NAV-900 Receivers).






HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA

AgRemote/RDI/Toolbox+ Configuration (AG-372, NAV-900 Receivers)

1. From the AgRemote home screen press  until **Configuration** displays.




2. Press  one time.

3. Press  until **DGPS Config** displays.


4. Press  until the **SBAS Sats** menu displays.

5. Press  to get the satellite name/ RN in edit mode.

6. Press  to make the satellite mode editable (cursor blinks on **Auto Heed**).




7. Press  until **Disabled** displays.




8. Press  to get the cursor blinking on the satellite name (**AORE**) again.




HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA

9. Press  until **PRN 135** displays.

10. Press  to make the satellite mode editable (cursor blinks on **Disabled**).



11. Press  until **Heed Health** displays.

12. Press the **Enter** button to confirm your changes and to leave the edit mode.

13. Press  several times to return to the AgRemote home screen.





HEAD OFFICE: 71301 LONDON ROAD, EXETER, ON N0M 1S3
WWW.DELTAPOWER.CA WWW.DELTAUSED.CA

Delta Power Equipment Contact Information:

For more information email dti@deltapower.ca or visit www.deltapowerprecision.com.

SOURCES: Trimble Agriculture April 2022 Service Bulletin

